

FIG. 1

# ASYMMETRIC HYBRID ACCESS SYSTEM AND METHOD

FIG. 1

## Field of Invention

This invention relates to systems and methods for extending a high-speed  
5 network to remote locations using an asymmetric hybrid access system.

## Background of the Invention

Current data communication systems typically use symmetric  
communication paths between transmit and receive sites, which have substantially  
10 the same data rates and use the same media in both directions. Such media may  
include coaxial, fiber optic, or telephone twisted-pair lines. Some networks  
alternatively use broadcast only paths. However, no current network combines the  
flexibility of full-duplex symmetric networks with the cost effectiveness of  
broadcast only networks.

Prior attempts at achieving asymmetric data communications included  
modems with very low speed return channels or systems combining a low speed  
broadcast channel with telephone return lines. However, no prior systems were  
able to extend a symmetric high-speed backbone network to remote locations at  
15 high speeds using an asymmetric hybrid access system. Known prior asymmetric  
systems are limited to low speed links.

It is desirable to develop a network which combines the flexibility of a full-duplex network with the effectiveness of a broadcast network at a reasonable cost.

5

### Summary of the Invention

According to the present invention, a high speed backbone network is extended for communications with remote locations with a hybrid asymmetric architecture having fully interactive duplex characteristics and including independent upstream and downstream communication <sup>Channels</sup>~~paths~~ operable at separately selectable speeds and protocols. According to one embodiment of the present invention, the hybrid asymmetric architecture includes 6 Megahertz television channels downstream and telephone lines for upstream communications. Alternative downstream communications can be accomplished according to the invention with a selected high bandwidth broadband service, including for example high definition television (HDTV). Downstream communications according to another embodiment can be implemented with a selected low cost, high speed broadband modem. Downstream communications can provide access to data from information sources including companies, government agencies, universities, libraries, and the like. Alternative upstream communications can be accomplished by a <sup>narrower</sup>~~narrow~~ band cable TV return channel, ISDN, radio, or a selected low-cost, low to medium speed telephone modem. The asymmetric hybrid system according to the present invention includes an interface with the backbone network connected to selected information sources. The interface includes point of presence (POP) circuits implementing high speed

downstream communications with lower speed upstream communications. The interface connects the backbone network with cable TV head ends, TV transmitters, cell sites, remote users, and upstream and downstream channels.

5           The present invention further includes a hybrid access configuration which uses both downstream and upstream channels. The present invention further includes a hybrid access configuration which uses downstream wireless TV channels and upstream public switch telephone network (PSTN), wireless RF communications or integrated services digital network (ISDN) telephone lines.

10          The present invention further includes a hybrid access configuration which uses both downstream and upstream cable TV channels. The present invention further includes a hybrid access configuration which has downstream satellite TV channels and upstream public switch telephone network (PSTN), wireless RF communications, or integrated services digital network (ISDN) telephone lines.

15           The present invention further includes packet and acknowledge suppression methods to eliminate redundant packet, byte, and acknowledge transmissions in a hybrid access system. A packet is defined as an information unit containing one or more bytes of information. Particularly according to the  
20          method of the present invention, a certain amount or number of data packets or bytes are enqueued or transmitted in a transmit-ahead window. Transmission of a window of bytes or packets is followed by a predetermined time-out period while the transmit queue awaits acknowledgments of packets received. To the extent receipt acknowledgments are received as to particular bytes or packets, these

packets and bytes in the transmit queue will be deleted from the transmit queue, and the transmit queue is open to receipt of further packets or bytes for emplacement in slots of the transmission queue for the deletions made. With respect to acknowledgments placed in a transmission queue, indications  
5 acknowledging receipt of later bytes and packets supersede acknowledgments of earlier transmitted bytes or packets. Accordingly, under the present invention, the earlier acknowledgments are deleted from an acknowledge transmission queue.

The present invention further includes an automatic address allocation and  
10 configuration method in transmissions employing a hybrid access system.

According to the present invention, remote users are identified initially with an abstract name, e.g., "Bob," and this abstract name is registered by the network management system. Configuration is established by the downstream routers polling the remote users and registering the location of the remote user responding  
15 to the poll made with the particular abstract name. Internet Protocol address and upstream channel allocation is accordingly accomplished subject to the configuration made including abstract name and identified location.

The present invention further includes a prioritized polling method in  
20 transmissions employing a hybrid access system. According to a method of the present invention, hybrid upstream routers poll client devices such as remote link adapters (i.e., "RLAs") according to predetermined priority levels. According to one embodiment of the present invention, priority levels are established for state categories of RLAs. According to one embodiment of the present invention,

priority level states include status states such as idle, non-responsive, requesting channel(s), active, or active-credit. According to one embodiment of the present invention, RLAs which request a channel are prioritized according to the amount of time its channel requests have gone unfulfilled. According to one embodiment  
5 of the present invention hybrid upstream routers poll downstream RLAs which are idle more frequently than non-responsive RLAs.

The present invention further includes an automatic gain adjustment technique in transmissions employing a hybrid access system, according to which  
10 a remote link adapter sends successive indications to a hybrid upstream router at selected different power levels. When a power level indication is received by a hybrid upstream router, the receiving hybrid upstream router confirms receipt of such indication to the sending remote link adapter which then registers an associated power level as qualified. According to one embodiment of the present  
15 invention, the selected different power levels are dynamically adjusted in magnitude of transmission level.

The present invention further includes a quality-based upstream channel allocation technique in transmissions employing a hybrid access system.

20 According to the technique, the hybrid upstream router first determines the availability of upstream cable channels by a frequency agile RLA setting a wide range of narrowband upstream channels. The upstream router then makes a quality assessment of available channels in view of most recent demand, and it finally selects an upstream channel in view of the quality assessment made.

Quality assessment includes determination of busy status and signal characteristics including error rates, noise floor, and signal to noise ratio.

Upstream channels are releasable according to inactivity or time-out criteria, according to which release or reassignment occurs responsive to inactivity for  
5 over a threshold period. Inactivity is assessed by the hybrid upstream router monitoring operability indications and data packets received from assigned RLAs.

The present invention further includes a credit allocation technique in transmissions employing a hybrid access system. According to a method of the  
10 present invention, an upstream channel is shared by a plurality of RLAs in accordance with a credit criterion, and credit control packets are dispatched to a RLA which permit the RLA to send data packets to arbitrary hosts. Upon sending a data packet, the RLA returns the credit control packet to a server containing software including Hybridware™ code which manages data flows. The  
15 Hybridware™ code or Hybridware™ server, according to one embodiment of the present invention, includes software distributed among data processors in the upstream and downstream routers and elsewhere in the HASPOP, including for example in the network management system.

## DESCRIPTION OF THE DRAWINGS

20 Figure 1 is a detailed schematic drawing of a hybrid access system connected to a backbone network such as the Internet, and having points of presence connecting the backbone network to cable TV headends, TV transmitters, or Logical Nodes (e.g., cell sites), with remote users connecting to an

RLA which in turn connects to downstream TV channels and independent lower speed upstream channels;

5 Figure 2a is a schematic drawing of a hybrid access system point of presence (POP) according to the present invention including at least a single host computer or server and at least a single router including a hybrid downstream router, a hybrid upstream router, a dial-up router, an Internet router, or a backbone network router, and a POP LAN switch;

10 Figure 2b is a block diagram of a downstream router according to the present invention;

15 Figure 2c is a block diagram of an upstream router according to the present invention;

FIGS. 3a, 3b, and 3c comprise a pictorial diagram of a hybrid access system according to the present invention according to which a remote user can communicate with an information provider through the hybrid access system;

20 Figure 4 is a logical data flow diagram showing data flows between a server and a client computer of the hybrid access system according to the present invention;

Figure 5 is a flow chart of operation of a two-way cable network

embodiment of the hybrid access system according to the present invention;

Figure 6 is a flow chart of operation of a one-way cable network  
embodiment of the hybrid access system according to the present invention,  
5 including provision for upstream telephone system data flow;

Figure 7 is a Hybridware™ server state diagram of the upstream channel  
allocation method according to the present invention;

10 Figure 8 is a Hybridware™ client state diagram of the upstream channel  
allocation method according to the present invention;

Figure 9 is a logical data flow diagram showing data flows between router  
server and client computers of the hybrid access system for automatic handling of  
15 multiple clients according to automatic address allocation methods of the present  
invention;

Figure 10 is a flow chart of address allocation control protocol according  
to the present invention;

20 Figure 11 is a state diagram of the hybrid adaptive gain control protocol  
according to the present invention;

Figure 12a is a transmission diagram of information exchange between



two nodes in an asymmetric network according to the present invention, having a high downstream data rate of  $n$  bits per second and a lower upstream data rate of  $m$  bits per second;

5        Figure 12b is a diagram of conventional downstream messaging of first through fourth data packets, 100, 250, 325, and 450, between first and second nodes, in parallel with upstream transmission of receipt acknowledge indications;

10        Figure 12c is a diagram of a conventional transmission buffer queue in a RLA of a remote client station;

15        Figure 12d is a diagram indicating a redundant acknowledgment packet in a conventional transmission buffer queue in a RLA of a remote client station;

20        Figure 12e is a diagram of a conventional transmission buffer queue, indicating no need for an earlier acknowledgment (ack 100) packet in view of a new acknowledgment (ack 210) packet that supersedes the earlier acknowledgment packet;

25        Figure 12f is a diagram of first through fourth network nodes serially connected to each other in accordance with the present invention, wherein the link between the second and third nodes is asymmetric and that between the first and second and the third and fourth nodes are symmetric;

Figure 13 is a tabular description of transmission control protocol/ Internet protocol (TCP/IP) data transmission packet protocol header as used in connection with the present invention;

5 Figure 14a is a diagram of a sequential data transmission between first and second network nodes, according to the present invention;

Figure 14b is a diagram of the contents of a conventional transmission queue in the downstream node during a first time period;

10 Figure 14c shows the contents of a transmission queue in a downstream node during a later time period, eliminating retransmission of the 300 packet, according to the present invention, because another 300 packet was already in the transmission queue;

15 Figure 15 is a flow diagram of the acknowledge suppression method according to the present invention;

20 Figure 16 is a flow diagram of the packet suppression method according to the present invention;

Figure 17 is a flow diagram of information exchanges between Hybridware™ server and client, under conditions in which the client has no information to transmit;

Figure 18 is a flow diagram of information exchanges between Hybridware™ server and client, under conditions in which the client has information to transmit and the server gradually allocates bandwidth to the client;

5 Figure 19 is a flow diagram of information exchanges between Hybridware™ server and client, under conditions in which the server allocates the client a dedicated channel, the client transmits data and periodically reports to the server with done messages; and

10 Figure 20 is a flow diagram of information exchanges between Hybridware™ server and client, under conditions in which a dedicated channel is converted into a shared channel.

### **Description of the Preferred Embodiment**

15 Figure 1 is a detailed schematic drawing of a hybrid access system 1 according to the present invention, showing a RLA and user workstation 29 connected through hybrid access system 1 to a variety of entities connected to a backbone network 20 such as Internet, including information providers 21, corporations 22, government agencies 23, universities 24, and others 25. A  
20 backbone network is one which is typically not directly connected to a user. Hybrid access system 1 according to an embodiment of the present invention includes hybrid access system (HAS) points of presence (POPs) 26 and other points of presence 27. HASPOPs 26 include individual HASPOPs 26(1)-26(3) which enable communication over a broadband network, either by upstream and

downstream cable communications or by downstream cable and upstream telephone communications or various other hybrid configurations (e.g., wireless or satellite). The present invention particularly includes (1) a hybrid access configuration which uses downstream cable TV channels and upstream public switch telephone network (PSTN), wireless RF communications or integrated services digital network (ISDN) telephone lines; (2) a hybrid access configuration which uses downstream wireless TV channels and upstream public switch telephone network (PSTN), wireless RF communications or integrated services digital network (ISDN) telephone lines; (3) a hybrid access configuration which uses both downstream and upstream cable TV channels; (4) a hybrid access configuration which uses both downstream and upstream wireless channels; and (5) a hybrid access configuration with downstream satellite channels and upstream PSTN, wireless RF communications or ISDN telephone channels.

Backbone network 20 such as the Internet which includes a plurality of Internet servers 20' connected to HASPOPs 26 each including a plurality of host computers and/or servers, collectively referred to as hybrid servers. Hybrid access system 1 further includes broadcast units such as, a cable television (TV) head end 28, independent upstream channels 28; and a RLA 29. U.S. Pat. No. 5,347,304 (1994) assigned to Hybrid Networks, Inc., and describing an example of an RLA is hereby expressly referenced and incorporated herein in its entirety. An RLA may receive analog broadcast signals including encoded digital information which the RLA decodes and provides to a data terminal or computer. According to an embodiment of the present invention, the downstream flow of information

proceeds from HASPOPs 26(1)-26(3) through cable TV head end or TV transmitters 28 or cell sites 30 and through RLA and user workstation 29.

Upstream information flow proceeds in one case from RLA and user workstation 29 through independent upstream channels 28; to HASPOP 26(1), and then to

5 backbone network 20; along T1 or T3 or other digital lines. In another case, upstream information proceeds from user workstation through RLA 29 through the cable TV network, and cable TV head end 28 to hybrid access system point of presence and then through T1, T3, or other digital lines to backbone network 20.

The outputs of the cable TV headends or TV transmitters 28 include pluralities of

10 high speed downstream broadband radio frequency, i.e., RF, channels connected to respective remote users 29. Hybrid access system 1 further includes a plurality

of cell sites 30 connected through high speed links to a corresponding hybrid

A 26 access system point of presence <sup>26</sup>3. The outputs of cell sites 30 include pluralities

of high speed downstream broadband channels connected to selected remote users

15 29. A particular remote user 29 can be connected via an independent lower speed upstream channel to a hybrid access system point of presence 26 as discussed

below or via a similar independent lower speed upstream channel to another point

of presence system 27. By lower speed it is meant at a speed reduced from the

speed of the high speed link used to transmit information downstream. A

A 20 particular hybrid access system point of presence <sup>26</sup>3 can be connected via duplex

high speed links to a plurality of cable TV headends or TV transmitters, to a

plurality of cell sites 30, or a combination of cable TV headends or TV

transmitters 28 and cell sites 30.

Figure 2a is a schematic drawing of a point of presence (POP) system 26(1) according to the present invention, including host computers or servers 39 and a POP local area network, i.e., LAN switch 33 to which host computers or servers 39 are connected. Further connected to LAN switch 33 are one or more downstream and one or more upstream hybrid access system point of presence routers, respectively 34 and 35, one or more dial-up routers 36, a network management system 37, and conventional routers 38. Connected to POP LAN switch 33 are one or more data storage elements or systems. Each downstream hybrid access system point of presence router 34 is connected with a high speed link to a TV transmitter or cable TV headend, for example. Further, each upstream hybrid access system point of presence router 35 is connected to a plurality of independent upstream channels, which operate at a lower speed than the downstream high speed links to TV transmitters or cable TV headends. Each dial-up router 36 is connected to a plurality of independent upstream channels operating at a lower speed than the indicated downstream high speed links. Each conventional router 38 is connected along a high speed line to wide area network (WAN) lines to selected information providers, Internet, or other nodes or businesses. POP LAN switch 33, according to one embodiment of the present invention is connected directly along a high speed line to wide area network (WAN) lines to selected information providers, Internet, or other nodes or businesses.

Figure 2b is a block diagram of hybrid downstream router 34 according to the present invention. In particular, downstream router 34 includes network

interface 34a, link interface 34b, physical interface 34c, controller 34d, physical  
interface 34e, link interface 34f, and network interface 34g. Downstream router 34  
and physical interface 34e are connected to POP LAN switch 33 for sending and  
receiving information, and physical interface 34e, link interface 34f, and network  
5 interface 34g are serially connected to each other and to controller 34d for  
bidirectional communication of selected information. Additionally, controller 34d  
is connected directly to each of physical interface 34e and link interface 34f along  
indicated lines to accomplish control and messaging functions. Downstream  
router 34 and physical interface 34c are connected to cable TV headends, TV  
10 broadcast sites, cell sites or the like, to communicate information primarily or  
exclusively in a unidirectional or downstream direction, and physical interface  
34c, link interface 34b, and network interface 34a are serially connected to each  
other and to controller 34d for selected communication of selected information.  
Additionally, controller 34d is connected directly to each of physical interface 34c  
15 and link interface 34b along indicated lines to accomplish control and messaging  
functions. Downstream router 34 may include one or more of physical interfaces  
34c. According to an embodiment of the present invention, router 34 may be a  
bridge without network interfaces 34a and 34g or a connection without network  
interfaces 34a and 34g and without link interfaces 34b and 34f. According to yet  
20 another embodiment of the present invention, router 34 can be a gateway.

Figure 2c is a block diagram of upstream router 35 according to the  
present invention. In particular, upstream router 35 includes network interface  
35a, link interface 35b, physical interface 35c, controller 35d, physical interface

35e, link interface 35f, and network interface 35g. Upstream router 35 and physical interface 35e are connected to POP LAN switch 33 for sending and receiving information, and physical interface 35e, link interface 35f, and network interface 35g are serially connected to each other and to controller 35d for  
5 bidirectional communication of selected information. Additionally, controller 35d is connected directly to each of physical interface 35e and link interface 35f along indicated lines to accomplish control and messaging functions. Upstream router 35 and physical interface 35c are connected to upstream channels, e.g., telephone links for example, to communicate information primarily or exclusively in a  
10 unidirectional or upstream direction, and physical interface 35c, link interface 35b, and network interface 35a are serially connected to each other and to controller 35d for selected communication of selected information. Additionally, controller 35d is connected directly to each of physical interface 35c and link interface 35b along indicated lines to accomplish control and messaging  
15 functions. Upstream router 35 may include one or more of physical interfaces 35c. According to an embodiment of the present invention, router 35 may be a bridge without network interfaces 35a and 35g or a connection without network interfaces 35a and 35g and without link interfaces 35b and 35f. According to yet another embodiment of the present invention, router 35 can be a gateway.

20  
Figures 3a-3b are drawings of a hybrid access system 1 according to the present invention according to which remote user having a workstation 2 or connected to LAN 61, as shown respectively in Figures 3b and 3c can communicate with a selected information provider 21 including LAN 50, bridge



or router 51 connected to LAN 50, and dial-up router 52 connected to LAN 50 through a hybrid access system point of presence 26. Further, HAS POP is connected along a high speed link to bridge or router 51. Additionally, HAS POP 26 is linked to other information providers to receive selected information items.

5 Additionally, dial-up router 52 is connected to a plurality of upstream channels. Figures 3b and 3c additionally show respective first and second users, in one case including workstation 2 in turn including a RLA 60 and in the other instance including RLA 60 and a local area network (LAN) 61 connected to RLA 60. First user 29(1) is connected to an upstream channel from user workstation 2, and  
10 second user 29(2) is connected to an upstream channel directly from RLA 60. In the case of each user, RLA 60 receives input information, particularly radio frequency (RF) information along one of respective input channels connected thereto.

15 Figure 4 is a logical data flow diagram showing data flows between a server and a client computer of the hybrid access system 1 according to the present invention. Hybrid access system 1 includes a server application 70, a hybrid system manager 71, and a Hybridware™ server 72 connected to LAN 38. Hybrid access system 1 further includes a Hybridware™ client 73 and a client  
20 application 74 operating with Hybridware™ client 73. Hybridware™ client 73 communicates with Hybridware™ server 72, as transmitter along upstream channel 75 or as receiver along downstream channel 76. Downstream data traffic is expected to be higher capacity than upstream data traffic: Hence, the bolder depiction of downstream channel 76 than upstream channel 75.

Figure 5 is a flow chart of operation of a two-way cable network embodiment of hybrid access system 1 according to a hybrid protocol embodiment of the present invention. In particular, according to one embodiment of the hybrid protocol of the present invention, client application 74 sends 100 data to server application 70 in an upstream direction, thereby issuing a connection request. Hybridware™ client 73 buffers the data received and checks if it controls an upstream data channel. If it does, then the data is transmitted forthwith. If it doesn't, Hybridware™ client 73 queues up the data message and creates 101 a channel request for a particular subchannel within upstream channel 75. Hybridware™ client 73 then waits 102 for a poll from Hybridware™ server 72, i.e., Hybridware™ router. According to an embodiment of the present invention, prioritized polling is conducted whereby not all clients are polled at the same frequency. Clients in an idle state are polled relatively frequently. Clients in blocked and NON-RESP states are polled but not at the same relatively high frequency. Clients in an ACTIVE state are not polled at all. This is based on the assumption that an active client has what it wants and that it is most important to respond quickly to new connections coming from clients in an IDLE state. Those clients coming from a NON\_RESP cycle receive second order attention and can wait a little longer, since they may have already been in a state where communication are impossible and may have been in that state for a considerable period of time. According to one embodiment of the present invention, a poll cycle is the smallest period such that all but active clients are polled at least once. Idle clients may be polled multiple times during one poll cycle. Blocked and non\_resp clients are distributed evenly across the poll cycle to assure that the

latency for acquiring a channel for idle units is uniform. All clients are grouped according to their state and polled within each group according to the round robin approach according which each of a series is polled in sequence and then the same sequence is repeatedly polled individual by individual. Upon receipt of a poll,

5 Hybridware™ client 73 sends 103 a channel request via lower speed upstream channel 75. Hybridware™ router 72, i.e., server, receives 104 the channel request from Hybridware™ client 73 and initially sends 105 a login message to Hybridware™ system manager 71. Hybridware™ system manager 71 verifies 106 that Hybridware™ client 73 is an authorized user of data processing services on  
10 the particular node or system within which hybrid access system 1 operates. Then, Hybridware™ router 72 receives 107 a login response message from Hybridware™ system manager 71 through LAN 38, which indicates whether the client is allowed to operate on the particular network and which contains other operating characteristics of Hybridware™ client 73. Hybridware™ router 72 then  
15 allocates 108 (see state diagrams of Figures 7 and 8) an upstream channel 75 for Hybridware™ client 73, depending on channel availability and suitability. Suitability depends on factors including but not limited to channel quality, type of service required, operating characteristics of Hybridware™ client 73,  
configuration restrictions, and the like. Hybridware™ router 72 sends 109 an  
20 upstream channel allocation message to Hybridware™ client 73 via high speed downstream channel 76, which may according to one embodiment of the present invention specify the frequency on which Hybridware™ client 73 is permitted to transmit. Thereafter, Hybridware™ client 73 receives 110 an upstream channel allocation. Next, Hybridware™ client 73 tunes 111 to the specifically allocated

upstream data channel frequency on which it is permitted to transmit data. Finally,  
Hybridware™ client 73 sends 112 the selected application data from client  
application 74. Accordingly, client application 74 and server application 70 are  
able to send and receive 113 data via upstream bandwidth management of an  
5 asymmetric hybrid access system, according to the present invention.

Figure 6 is a flow chart of operation of a one-way cable network  
embodiment of the hybrid access system 1 according to the present invention,  
including provision for upstream telephone system data flow. According to this  
10 embodiment of the present invention, when client application 74 needs to  
communicate with server application 70 in an upstream direction, Hybridware™  
client 73 dials 202 Hybridware™ router 72. Then, Hybridware™ client 73 sends  
203 a channel request via lower speed PSTN upstream channel (not shown).  
Hybridware™ router 72 receives 204 the channel request and sends 205 a login  
15 message to Hybridware™ system manager 71. Hybridware™ system manager 71  
verifies 206 Hybridware™ client 73 as an authorized user. Then, Hybridware™  
router 72 receives 207 a login response from Hybridware™ system manager 71.  
Hybridware™ router 72 sends 208 an authorization message to Hybridware™  
client 73 via high speed downstream channel 76. Hybridware™ client 73 receives  
20 209 the authorization message for use of a selected upstream PSTN channel.  
Finally, Hybridware™ client 73 sends 212 the selected application data.  
Accordingly, client application 74 and server application 70 are able to send and  
receive 213 selected data via the asymmetric hybrid access system 1.

Figure 7 is a Hybridware™ server state diagram for upstream channel allocation of the hybrid access system according to one embodiment of the present invention. According to the state diagram of Figure 7, the Hybridware™ server can be in one of four states: IDLE 301, NON\_RESP 304, BLOCKED 302, or  
5 ACTIVE 303. In the IDLE state, the Hybridware™ server expects an IDLE poll response. If there is no request to the client from the application or a channel request message, or if there is application data that needs to be sent in the upstream direction. Upon receiving a channel request message, the server transitions the client to a BLOCKED state. In a BLOCKED state, the server sends  
10 one of two messages to the client, a channel allocation message or a no channel available message. Upon sending a channel allocation message, the server transitions the client to an ACTIVE state. Upon sending a no channel available message, the client remains in a BLOCKED state. The client will remain in the BLOCKED state until either a channel becomes available in which case the server  
15 will transition the client to the ACTIVE state or the server receives a channel release message in which case the server will transition the client to the IDLE state. In the ACTIVE state, the server does not poll the client. The server transitions the client from ACTIVE to IDLE upon receiving a channel deallocation message or upon detecting a system defined inactivity time-out. In  
20 the ACTIVE state, the server waits for a periodic heartbeat message from the client. The Hybridware™ server software awaits periodic heartbeat messages from the client at selected time intervals. The server software monitors other channel quality parameters including errors and signal to noise ratios. If the server stops hearing a certain number of operability indications or signals within a system

defined interval as to a particular client, or if particular parameters (e.g., signal to noise ratio) exceed a predetermined threshold , then the server sends a directed poll to the particular client. Essentially, the client is instructed to respond on another control frequency. If the client responds on the designated control frequency, the server reassigns the upstream channel to the client, so that it can continue to operate. If not, the client is deemed NON\_RESP. Channel quality monitoring and channel reassignments are done transparently to the user and the applications. If a certain, system defined, consecutive count of heartbeat messages is missed, the server issues a special poll message or directed poll. If the client does not respond, the server transitions to the NON\_RESP state. If the client responds to the poll, the server either remains in the ACTIVE state or transitions to the IDLE state. The former happens, if the client responds with a channel request message, and the latter happens, if the client responds with an IDLE poll response. In the former case, the server may decide to assign a different upstream channel to the client. In the BLOCKED or IDLE state, the server will transition the client to NON\_RESP, i.e., "non-responsive," state after the client fails to respond to a system defined number of polls. The NON\_RESP state is almost identical in terms of state transition to idle state, a difference being that an IDLE poll response transitions the client into an IDLE state.

Figure 8 is a Hybridware™ client state diagram for upstream channel allocation of the hybrid access system 1 according to an embodiment of the present invention, involving two way cable communication. According to this embodiment, the hybrid upstream client protocol has three states, IDLE 401,

CON\_REQ, i.e., "connect request" 402, and ACTIVE 404. In the IDLE state, the client, when polled, will transmit an IDLE poll response, if there is no request from the application. However, it will respond with a channel request message, if there is data that needs to be sent upstream. Upon transmitting a channel request message, the client transitions to a CON\_REQ state. In the CON\_REQ state, the client expects one of two messages from the hybrid router, a channel allocation or a no-channel allocation signal. Upon receiving a channel allocation message, the client informs the application and tunes to the channel it was allocated and transitions to the ACTIVE state. Upon receiving a no-channel available message, the client informs the application and transitions to the IDLE state. In the ACTIVE state, the client forwards data messages from the application to the upstream transmitter. In the ACTIVE state, the client further monitors the application activity and if it detects that no data has moved from the application to the upstream transmitter for a system defined period of time, it will send a channel deallocation request and transition to an idle state. In an ACTIVE state, the application may explicitly request that the channel be released, in which case the client will send a channel deallocation request to the hybrid router and will transition to the IDLE state. In the ACTIVE state, the client periodically sends an operability indication message to the server. If the client receives a poll message during the ACTIVE state, it will send a channel request message and will transition to a CON\_REQ state. The hybrid router may also send an unsolicited channel release message, in which case the client will notify the application and transition from ACTIVE state to IDLE state.

Figure 9 is a logical data flow diagram showing data flows between server and client computers of the hybrid access system 1 according to the present invention, for multiple clients under an address allocation protocol simplifying distribution of IP addresses to remote systems. The protocol according to the present invention determines where a given Hybridware™ client is located and how to download its IP address, given that the client has no address yet. Hybrid access system 1 includes a server application 70, a hybrid system manager 71, and Hybridware™ servers 72a & 72b connected to LAN 38. Hybrid access system 1 further includes Hybridware™ clients 73a and 73b and client applications 74a and 74b operating with respective ones of Hybridware™ clients 73a and 73b. Hybridware™ client 73a communicates with Hybridware™ server 72a, as transmitter along upstream channel 75a or as receiver along downstream channel 76a. Hybridware™ client 73b communicates with Hybridware™ server 72b, as transmitter along upstream channel 75b or as receiver along downstream channel 76b. Downstream data traffic is expected to be higher capacity than upstream data traffic: Hence, the bolder depiction of downstream channels 76a and 76b than upstream channels 75a and 75b.

Figure 10 is a flow chart of address allocation control according to an embodiment of the present invention to logon and configure Hybridware™ clients with a selected unique node name which is entered in the configuration database in the hybrid system manager 71 which is the software portion of network management system 37. In particular, hybrid system manager 71 sends a new client message to all hybrid routers 72a and 72b after learning of particular new



clients by message, mail, or telephone call (step 500 in Figure 10). At this point the hybrid system manager is aware of a Hybridware™ client identification name and equipment serial number, but has not associated the client identification name with a separate unique client address (e.g., Internet Protocol, or IP address)

5 provided by separate automatic registration. Each hybrid router 72a and 72b periodically broadcasts a configuration poll message (step 501). Hybridware™ clients recognize their preselected unique names during a configuration poll (step 502). Hybridware™ clients 72a and 72b respond to the configuration poll.

Hybrid routers 72a and 72b receive respective configuration poll responses. Then,

10 hybrid routers 72a and 72b send respective client found messages to system manager 71. System manager 71 then sends a cease configuration poll message to all hybrid routers. Further, system manager 71 allocates an Internet protocol (IP) address and other configuration data for each new client according to the preselected unique names. System manager 71 sends the IP address and other  
15 configuration data to the applicable hybrid router 72a, 72b. Then, the applicable hybrid router 72a, 72b sends, using broadcast or unicast and the unique name, the corresponding IP address and other configuration data to the applicable Hybridware™ client. As a result, the Hybridware™ client receives the IP address and other configuration data determined and reconfigures appropriately. In

20 summary, according to the present invention, an automatic address allocation and configuration method in transmissions employs a hybrid access system. Remote users are identified initially with a unique abstract name, e.g., "Bob," and this abstract name is registered by the network management system. Configuration is established by the upstream routers polling the remote users and registering the

location of the remote user responding to the poll made with the particular abstract name. Upstream channel allocation is accordingly made subject to the configuration made including abstract name and identified location. Automatic address allocation and configuration is accordingly accomplished on line at an initial log-on session with a new user. The method of the present invention is accordingly swift and simple, eliminating registration delays experienced by many known log-in systems.

Figure 11 is a state diagram of the hybrid adaptive gain control protocol according to the present invention, which overcomes noise and attenuation while transmitting on cable in an upstream direction. The hybrid adaptive gain control protocol has a SEARCHING state 600 and a STABLE state 601. In the STABLE state 601, the protocol evaluates poll messages from the hybrid router. If a poll message indicates loss of a poll response, the protocol transitions to the SEARCHING state 600. Poll responses are transmitted at a fixed power level. In the SEARCHING state 600, the client system responds to polls with a poll response at larger and larger power levels. After receiving a system specified, number of consecutive polls with an indication of a successful poll response, the system transitions to the STABLE state.

Figure 12a is a transmission diagram of information exchange between nodes A and B. Nodes A and B comprise an asymmetric network according to the present invention, having a high downstream data rate of  $n$  bits per second and a lower upstream data rate of  $m$  bits per second. The downstream data rate  $n$  is

greater than the upstream data rate  $m$ . Node B includes receive and transmission queues to hold information received and to be sent, including acknowledge indications or messages. The acknowledge suppression method according to the present invention relates to the node or system transmitting data

5 acknowledgments, which acknowledges receipt of either data packets or data bytes contained in incoming packets. The numbers on data packets indicate the position of the last data byte of the packet in the data stream, and the acknowledgment numbers indicate that all the bytes of the data stream up to and including the byte indicated have been received. According to the method of the present invention, the acknowledgment of byte  $k$  (or packet number  $k$ ) indicates  
10 that all bytes or packets prior to  $k$  have been received. According to a method of the present invention, the transmit queue queues up additional acknowledgment packets as new packets are received. Figure 12b is a diagram of messaging of first through fourth data packets, 100, 250, 325, and 450, between upstream and  
15 downstream nodes, in parallel with upstream transmission of receipt acknowledge indications with respect to only two data packets, namely 250 and 450. Figure 12c is a diagram indicating acknowledgment of first and second packet receptions during a first time period. In particular, packet 1 (i.e., "pkt 1") is currently being sent, and an acknowledge (i.e., "ack 250") message is currently being appended at  
20 the end of the transmit queue. Figure 12d is a diagram indicating acknowledgment of another packet during another period. Figure 12e is a diagram indicating no need for an acknowledge 100 signal in view of a subsequent acknowledgment having been successful. In particular, according to the acknowledge suppression method of the present invention, not all acknowledgment packets will be sent to

node A, because the "ack 210" message carries information which supersedes the "ack 100" message. Accordingly, the amount of traffic on the communication link from B to A is reduced, according to the present invention. In general, this introduces an acknowledge latency, but where all messages queued up for transmission are acknowledgments, acknowledgment latency is reduced. For example, when an "ack 15" signal is transmitted and an "ack 100" message awaits transmission, and an "ack 210" message is appended to the queue, the acknowledge suppression method according to the present invention will delete the "ack 100" message as superfluous. Any new acknowledgments appended while "ack 15" is being transmitted will result in deletions of unnecessary acknowledgments keeping queue length to two. Upon transmit completion of "ack 15," the next acknowledgment, e.g., "ack 210" will be transmitted. Accordingly, the method of the present invention eliminates unnecessary transmission of "ack 100" signals and provides for reduced acknowledgment latency for "ack 210." The acknowledge suppression method according to the present invention, accordingly reduces the probability of queue overflow and potential out of memory conditions in system B. It reduces the load on the communication link from B to A, and in some circumstances reduces acknowledgment latency for data transfers from B to A.

Figure 12f is a diagram of first through fourth network nodes serially connected to each other in accordance with the present invention, wherein the link between the first and second nodes is symmetric, the link between the second and third nodes is asymmetric and that between the third and fourth nodes is symmetric. The acknowledge suppression method of the present invention applies to both the communications system of Figure 12a, in which nodes A and B are end nodes, as

well as to the communications system of Figure 12f, in which nodes B and C are intermediate systems such as a router, and data packets originating at node D are transmitted through router nodes C and B to a central system connected to node A.

5

Figure 13 is a tabular description of a transmission control protocol/Internet protocol (TCP/IP) data transmission packet protocol header as used in connection with the present invention. The first five 32 bit words and the following IP options are referred to as the IP header. The five words following the IP options together with the words containing TCP options are referred to as the TCP header. The non-ack TCP header is the TCP header less the acknowledgment number field.

10

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204

later time period, eliminating retransmission of the 300 packet, because another 300 packet was already in the transmission buffer.

Figure 15 is a flow diagram of an acknowledge suppression (AS) method, i.e., an AS method, according to the present invention in which receipt of information transmitted from system A to system B over a first independent simplex communication link is acknowledged by system B. The method of the present invention starts 1500 at a particular time, and a first packet  $M_i$  of information is received 1501. If the transmit queue is not empty 1502, the header of the last packet  $M_{i+1}$  on the transmit queue is obtained 1503. If the transmit queue is empty 1502, then  $M_i$  is enqueued 1509 and the AS method according to the present invention is completed. If the header of the next packet  $M_{i+1}$  on the transmit queue equals 1504 the header of packet  $M_i$ , and the NON-ACK TCP header of  $M_i$  equals 1505 the NON-ACK TCP header of  $M_i$ , then  $M_{i+1}$  is discarded 1506. If the header of the last packet  $M_{i+1}$  on the transmit queue does not equal 1504 the header of packet  $M_i$ , or the NON-ACK TCP header of  $M_i$  does not equal 1505 the NON-ACK TCP header of  $M_i$ , then  $M_i$  is enqueued 1509 and the AS method according to the present invention is completed. If  $M_{i+1}$  is not the last message on the queue 1507, then the header on the next packet  $M_{i+1}$  on the transmit queue is obtained 1508, and a comparison is done to determine whether the header of the last packet  $M_{i+1}$  on the transmit queue equals 1504 the header of packet  $M_i$ . If  $M_{i+1}$  is the last message on the queue 1507, then  $M_i$  is enqueued 1509 and the AS method according to the present invention is completed.

Figure 16 is a flow diagram of the packet suppression (PS) method according to the present invention. The method of the present invention starts 1600 at a particular time, and a first packet  $M_i$  of information is received 1601. If the transmit queue is not empty 1602, the header of the last packet  $M_{i+1}$  on the transmit queue is obtained 1603. If the transmit queue is empty 1602, then  $M_i$  is enqueued 1609 and the PS method according to the present invention is completed. If the header of the last packet  $M_{i+1}$  on the transmit queue equals 1604 the header of packet  $M_i$ , then  $M_{i+1}$  is discarded 1606. If the header of the last packet  $M_{i+1}$  on the transmit queue does not equal 1604 the header of packet  $M_i$ , then  $M_i$  is enqueued 1609 and the PS method according to the present invention is completed. If  $M_{i+1}$  is not the last message on the queue 1607, then the header on the next packet  $M_{i+1}$  on the transmit queue is obtained 1608, and a comparison is done to determine whether the header of the last packet  $M_{i+1}$  on the transmit queue equals 1604 the header of packet  $M_i$ . If  $M_{i+1}$  is the last message on the queue 1607, then  $M_i$  is enqueued 1609 and the PS method according to the present invention is completed.

Figure 17 is a flow diagram of information exchanges between Hybridware™ server and client, according to conditions in which the client has no data to transmit. A credit (1, F) corresponding to a single predetermined amount of data, e.g., ten bytes, or ten packets, at a selected frequency F is transmitted from node A to node B, and a done signal DONE(0,0) is transmitted from node B to node A, indicating that no data packet was transmitted, leaving the existing credit level of the particular channel unchanged. The credit protocol according to

the present invention permits single upstream cable channels to be shared by multiple remote link adapters. Alternatively, a single upstream channel is controlled and used by a single remote link adapter until the channel is relinquished. The present invention includes an allocation method in transmissions employing a hybrid access system. According to a method of the present invention, an upstream channel is shared by a plurality of remote link adapters in accordance with a credit criterion, and credit control packets are dispatched to a remote link adapter which permit the remote link adapter to send data packets to arbitrary hosts. Upon sending a data packet, the remote link adapter returns the credit control packet to a Hybridware™ server. A credit permits a remote link adapter to send a certain number of packets up to a maximum number controlled by a configuration parameter MAX.\_CREDIT\_PACKETS, thereby eliminating polling for that period. If a remote link adapter does not have a data packet to send, it returns the credit to the hybrid access system without sending any data packets. The remote link adapter then sets a field in the credit control packet to the number of packets which was sent. If the protocol process at the server does not receive credit status information from the credit control packet within a certain credit time-out, CREDIT\_TIMEOUT, in milliseconds, for a certain number of times, FAIL\_CNT, consecutively, the remote link adapter is assumed to be in error and is put in a not-responding state (NON\_RESP). The overall upstream channel performance of a remote link adapter using a credit channel is lower than a remote link adapter on a sole use upstream channel. If any sole use upstream channel becomes available, this channel is given to the credit remote link adapter that has been waiting the



longest for a sole use upstream channel that currently has packets to send.

Figure 18 is a flow diagram of information exchanges between Hybridware™ server and client, according to conditions in which the client has information to transmit and the server gradually allocates bandwidth to the client. In particular, a node first provides a single credit at a selected frequency F. Then a packet is sent, consuming the credit, followed by a completion message indicating use of one credit and potential for an additional transmission corresponding to three credits. Next, a credit is provided corresponding to two packets at the selected frequency F, which is followed by two packet transmissions and a completion message indicating consumption of two credits and potential for transmission of one more. In response, another double credit is sent, followed by a single packet and an acknowledgment of transmission of one and potential for no more transmissions.

Figure 19 is a flow diagram of information exchanges between Hybridware™ server and client, according to conditions in which the server allocates the client a dedicated channel, the client transmits data and periodically reports to the server with done messages. In particular, a credit indication dedicating a channel at frequency F is provided, followed by 235 packet transmissions. According to prearrangement, a operability indication in the form of a DONE message is provided at an established time indicating potential for five more packet transmissions. The done message indicates completion of 235 packet transmissions, as an accounting function. Because the channel is dedicated,

further packet transmissions are made without specific further credit allocations.

Figure 20 is a flow diagram of information exchanges between Hybridware™ server and client, according to conditions in which a dedicated channel is converted into a shared channel. In particular, a credit indication code D indicating a dedicated channel at frequency F is provided, followed by transmission of 235 packets and a credit message stopping channel dedication and switching to a credit mode. Responsive to the credit message a DONE signal accounts for the 235 packets transmitted during the dedicated mode and indicates potential for five more transmissions. This is followed by a credit allocation of one at a selected frequency. Thus, one packet is transmitted, followed by a completion indication specifying potential for four more packets to be transmitted.